# LTECH





FC CE ROHS (warranty 5 years) Q

M series LED controller is compatible with 8 kinds remotes of different function (patent technology). which means using one receiver could experience single color/CT dimming, RGB/RGBW adjustment to meet customers' different lighting requirements. With the RF remote, speed/brightness adjustment. customise color and lighting changing modes selection could all be achieved


#### 1. Parameter:

Remote(RGBW	):
-------------	----


Model:	M4/M8
Working Voltage:	3Vdc (battery CR2032)
Working Frequency:	433.92MHz
Remote Distance:	30m
Working Temp .:	-30° <b>C~</b> 55° <b>C</b>
Weight(N.W.):	42g

Model:	M4-5A		
Input Voltage:	12~24Vdc		
Current Load:	5A×4CH Max 20A		
Max Output Power:	(060W~120W) × 4CH		
Protection:	Short circuit / Over-load		
Working Temp .:	-30° <b>C~</b> 55° <b>C</b>		
Weight(N.W.):	125g		

2. System Diagram:



#### 3. Product Size:



## LTECH



#### 4. The Learning ID Method of Remote Control:

Remote control has been matched to the receiver before leave factory, if deleted accidentally, you can learn ID as follow.

Learning ID: Short press ID learning button on the M4-5A receiver, the running light is on, then press any key on the M4/M8 remote control, the running light flashes several times, activated.


Cancel ID: Long press ID learning button on the M4-5A receiver for 5 seconds.

Attn: one receiver can be matched with max 10 same or different kinds remote.

#### 5. Operating Instruction for Receiver :



#### 6. Operating Instruction for Remote Control :



#### M4 Changing Mode Table

No.	Mode	Instrutcion	No.	Mode	Instrutcion
1	Static Red	Brightness Adjustable	7	Static White	Brightness Adjustable
2	Static Green	Brightness Adjustable	8	RGB Skipping	Speed/Brightness Adjustable
3	Static Blue	Brightness Adjustable	9	7 Colors Skipping	Speed/Brightness Adjustable
4	Static Yellow	Brightness Adjustable	10	RGB Color Smooth	Speed/Brightness Adjustable
5	Static Purple	Brightness Adjustable	11	Full-color Smooth	Speed/Brightness Adjustable
6	Static Cyan	Brightness Adjustable	12	Static Black	White light can be turn/off and adjusted

### 7. Wiring Diagram:

